

## Firmware upgrade 1.3.1

### Instructions For the Wolverine ESP

- 1- After downloading the firmware file, unzip (extract) the file and save the file FREFK131.MMV to the ESP's "Data" folder.
- 2- Disconnect the ESP from the computer.
- 3- From the "Home Screen" scroll down to the second page and press <OK> on the Wolverine Drive and press <OK> on the "Data" folder.
- 4- Press <OK> on the file FREFK131.MMV to run the firmware update program.
- 5- Follow on screen instructions.

#### 1.3.1 Firmware Upgrade Note:

Firmware version 1.3.1 fixes or adds the following:

RAW Image Support for:

1. 14 bit Nikon D3 & D300
2. Canon 450D
3. Canon 450D kill X2
4. Canon Power Shot G9
5. Sony Alpha 700
6. Sony A350 raw
7. Canon 1Ds Mark III CR2
8. Olympus E3 digital
9. Olympus E410 RAW
10. Olympus Evolt-510
11. Panasonic DMC-2
12. Panasonic DML L1
13. Panasonic FZ18
14. Panasonic FZ30

Oct. 2008