# Wolverine ESP Cradle System

User Manual Version 1.0 August, 2006



### **FEATURES**

- *Solution Set Use the ESP Cradle system to record directly from TV, DVD Player, VCR or any video source and watch them anywhere, anytime*
- Record hours of TV programs to the Wolverine ESP and enjoy the programs you watch every day on the go. Bring last night's game, cartoons or an entire season of your favorite series with you, anywhere
- *It's easy just follow the on-screen directions to set up the timer and Wolverine ESP will turn on to record and turn off when recording is complete*
- Solution Use the ESP Cradle as a stand to view, to charge, to connect to a computer and to connect to any video or audio source

## 1. System & Connections



- 1. Power Adapter Input Jack: Connect to the ESP power adapter
- 2. USB Jack: Connect to the ESP's USB cable
- 3. AV In: Connect to the Cradle AV Cable to record from TV's or other devices' "Audio/Video-Out"
- 4. AV Out: Connect to the Cradle AV Cable to connect to TV's or other devices' "Audio/Video In"



### 2. How To Record Video to the ESP

Record video while power adapter connected to the Cradle.

- ? Connect the Power Adapter into the Cradle's "DC 5V" labeled Jack
- ? Connect the AV Cable into the "AV IN" Jack
- ? Connect the AV Cable Red and White connectors to the "Audio-Out" Jack on the TV/DVD/VCR/etc.
- ? Connect the AV Cable Yellow connector to the "Video-Out" Jack on the TV/DVD/VCR/etc.
- ? Dock the ESP gently into the Cradle system
- ? Turn On the Wolverine ESP
- ? From the "Home Screen" as seen below select "VideoRec"
- ? After ESP acquires video signal press <MENU> to select quality of recording in pixels (for optimum file size/video quality choose 320x240 normal or fine)
- ? Press Joystick to start recording Recording dot at the bottom of the screen will turn from green to red while recording



- ? Press Joystick to pause or resume recording
- ? Press <ESC> to save recording to ESP hard drive

### 3. How To Setup Recording Schedules

#### Setting Date and Time

- ? From the "Home Screen" click on "Options"
- ? Click on "Time Zone" using the Volume (+)/(-) button select your time location from the preset world locations. <Press> Joystick to set
- ? Click on "Date Time" Set Date and Time, use Joystick to select date and time field and use Volume button (+) or (-) to increase or decrease. <Press> Joystick to select

SYSTEM DISPLA	Y VERSION
Language	English
Auto Shutdown	3
Hard Disk Sleep Timer	40
Copy Speed (HD)	Normal
Copy Speed (CF)	Normal
USB Mode	MSC Device
Time Zone VOIV	PST UTC-8
Date Time 200X/XX	XX:XX:XX XX/
စ်စ	Œ

Set Recording Schedules

You could schedule up to 8 different recording sessions. To set a record schedule:

- ? From the "Home Screen" select "VideoRec"
- ? Select "Schedule"



- ? Select any of "Schedule 1" through "Schedule 8"
- ? Select "Set REC Schedule"

	Video	Record List
\$	Schedule 1	200x/xx/xx xx:xx
Γ	Schedule 2	
Γ	Schedule 3	
Ľ	Schedule 4	
E	Schedule 5	
Γ	Schedule 6	
Γ	Schedule 7	aluarina
	Schedule 8	orvenne
E	Schedule 9	
2000	0	а

Video F	Record List
Schedule 2	
Storage	HD
Quality	320x240 Fine
Start Time	200x/xx/xx xx:xx
End Time	200x/xx/xx xx:xx
Remain Time	verinexxx
Planned Time	XXXXX
>0	XXXX CT

Schedule	Choose between eight different time schedules
Storage	Choose between HDD or memory card (when inserted)
Quality	<press> Joystick to select and use Volume button (+) or (-) to select quality of video in pixels (for optimum</press>
	file size to video quality choose 320x240 normal or fine)
Start Time	<press> Joystick to select and set recording start date and time</press>
End Time	<press> Joystick to select and set recording end date and time</press>
Remain Time	Remaining available total recording time
Planned Time	Total planned recording time

? After selecting all schedules press <ESC> to reach the "Home Screen" to properly save recording schedule(s).

Before recording time is due, place the ESP in the Cradle system, connect power adapter, connect the AV cable to the Cradle and other end into the TV's/DVD's/VCR's etc. video-OUT and Audio-Out source. The ESP will turn "On" one minute before set-to-record time and start recording at actual set time. Make sure the TV is turned ON at the time of recording.

The ESP will stop recording at the set "End Time" and turns off if the unit is set to turn off per the "Auto Shutdown Timer" (adjusted from under "Option"> "Auto Shutdown Timer").

? To play back recorded video from the "Home Screen" select "VideoRec" and choose "Playback". Video files are assigned alphanumeric file names, i.e. VREC0001, VREC0002, etc. Video files could me renamed after connecting the ESP to a computer.

#### NOTE:

Recording video from TV/DVD/VCR require converting an analog signal to a digital file. This conversion requires intense processing power. The ESP is a portable device that has limited processing power. Such limitation could produce a video with missed frames or incorrect sync of audio to video. Selecting a reduced output video quality may eliminate or minimize this issue.

#### 4. Playback through TV

The ESP Cradle system could be used to connect the ESP to a TV/Projector for external large screen display.

- ? Connect the Power Adapter to the Cradle into the "DC 5V" labeled Jack
- ? Connect the AV Cable into the "AV OUT" Jack on the Cradle
- ? Connect the AV Cable Red and White connectors to the "Audio-IN" Jack on the TV/Projector
- $? \quad \mbox{Connect the AV Cable Yellow connector to the "Video-IN" Jack on the TV/Projector.}$
- ? Select the appropriate TV Channel to receive the Audio/Video-In signal
- ? Dock the ESP into the Cradle system
- ? Turn On the Wolverine ESP
- ? From the "Home Screen" go to "Options"
- ? Select and Press "Cradle AVOUT" and using the joystick switch the "OFF' option to "ON" as displayed in below figure

File View Mode	Auto
View Screen Saver Timer	40
Screen Brightness	0
Text	White
Cursor Color	Yellow
TV Standard	NTSC-1
Cradle AVOUT	OFF
Reset Background	
0	CT.

Turning the "Cradle AVOUT" to "ON" will switch the display from the ESP screen to the TV screen.

#### **TECHNICAL SUPPORT**

For technical support, warranty service, or paid service please contact Wolverine Data at <u>Support@wolverinedata.com</u> or by calling 949-251-9888 M-F 9:00-5:00 PST